

Overview

The 50xR series accommodates one, two, or three rack cards in a durable standalone enclosure. They permit local standalone mounting of modules that are normally available as rack cards.

Convert Rack Cards to Standalone Modules

These enclosures are designed specifically to enable users of rack-mounted links to combine these cards and create a standalone fiber optic unit or system.

Standard Features

- Compact enclosures for rack cards
- Allows individual or combined operation
- Converts rack cards to standalone modules
- Supports up to three 1-inch cards
- Operate on 13.5 VDC
- Optional power adapter, standard or heavy duty

Standalone Enclosures

50xR



GE Security

U.S.
T (561) 998-6100
T 888-GE-SECURITY
888-(437-3287)
F 561 998 6224

Canada
T 519 376 2430
F 519 376 7258

Asia
T 852-2907-8108
F 852-2142-5063

Australia
T 61-3-9239-1200
F 61-3-9239-1299

Europe
T 32-2-719-9847
F 32-2-719-9846

Latin America
T 305-593-4301
F 305-593-4300

www.gesecurity.com

© 2005 General Electric Company
All Rights Reserved

Specifications

Electrical	
Input Power	13.5 VDC regulated
Current Requirement	Depends on card(s) installed
Power Consumption	Depends on card(s) installed
Power Connector	Detachable 3-pin screw terminal
Optional Power Supply	Model 613P or Model 614P

Mechanical	
Dimensions, (LWD)	9.31" x 6.33" x 1.15"
1-Card Enclosure	237 x 161 x 29 mm
Dimensions, (LWD)	9.31" x 6.33" x 2.15"
2-Card Enclosures	237 x 161 x 55 mm
Dimensions, (LWD)	9.31" x 6.33" x 3.15"
3-Card Enclosures	237 x 161 x 81 mm
Weight	0.81 lbs. (0.37 kg)
Weight,	0.97 lbs. (0.44 kg)
Weight, 3-Card Enclos.	1.14 lbs. (0.52 kg)
Material	Aluminum
Mounting	Provisions for 4 mounting screws


1-Card Enclos.
2-Card Enclos.

Related Diagram

Not
Applicable

Ordering Information

Use the Configurator below to select the options available for this product.



Card Capacity

- 1 One 1-inch rack card
- 2 Two 1-inch rack cards (one 2-inch rack cards)
- 3 Three 1-inch rack cards (one 3-inch rack cards)

As a company of innovation, GE Security reserves the right to change product specifications without notice. For the latest product specifications, visit www.GESecurity.com or contact your GE Security sales representative.
5xxR-2006-09-2



imagination at work