

DVR 60 Sample Analog/IP Configurations

Analog (4CIF)	IP SD (4CIF)	UltraView Camera (4CIF)	IP HD 720p (1280x720)	IP HD 2MPX (UXGA - 1600x1200@12.5fps max)	Max. Amt of cameras connected
16	8				24
16	4		2		22
16	4			2	22
16			4		20
16			2	2	20
16				4	20
16		8			24

Analog (4CIF)	IP SD (4CIF)	UltraView Camera (4CIF)	IP HD 720p (1280x720)	IP HD 2MPX (UXGA - 1600x1200@12.5fps max)	Max. Amt of cameras connected
14	9				23
14	5		2		21
14	5			2	21
14	1		4		19
14	1		2	2	19
14	1			4	19
14		9			23

Analog (4CIF)	IP SD (4CIF)	UltraView Camera (4CIF)	IP HD 720p (1280x720)	IP HD 2MPX (UXGA - 1600x1200@12.5fps max)	Max. Amt of cameras connected
12	10				22
12	6		2		20
12	6			2	20
12			5		17
12			1	4	17
12	2			4	18
12		10			22

Analog (4CIF)	IP SD (4CIF)	UltraView Camera (4CIF)	IP HD 720p (1280x720)	IP HD 2MPX (UXGA - 1600x1200@12.5fps max)	Max. Amt of cameras connected
10	11				21
10	5		3		18
10	7			2	19
10	1		5		16
10	3		2	2	17
10	1		1	4	16
10		11			21

Analog (4CIF)	IP SD (4CIF)	UltraView Camera (4CIF)	IP HD 720p (1280x720)	IP HD 2MPX (UXGA - 1600x1200@12.5fps max)	Max. Amt of cameras connected
8	12				20
8	6		3		17
8	6		1	2	17
8			6		14
8			2	4	14
8				6	14
8		12			20

Analog (4CIF)	IP SD (4CIF)	UltraView Camera (4CIF)	IP HD 720p (1280x720)	IP HD 2MPX (UXGA - 1600x1200@12.5fps max)	Max. Amt of cameras connected
6	13				19
6	7		3		16
6	7		1	2	16
6	1		6		13
6	1		2	4	13
6	1			6	13
6		13			19

Analog (4CIF)	IP SD (4CIF)	UltraView Camera (4CIF)	IP HD 720p (1280x720)	IP HD 2MPX (UXGA - 1600x1200@12.5fps max)	Max. Amt of cameras connected
4	14				18
4	8		3		15
4	2			6	12
4			7		11
4			1	6	11
4	2			6	12
4		14			18

Analog (4CIF)	IP SD (4CIF)	UltraView Camera (4CIF)	IP HD 720p (1280x720)	IP HD 2MPX (UXGA - 1600x1200@12.5fps max)	Max. Amt of cameras connected
2	15				17
2	9		3		14
2	7			4	13
2	1		7		10
2	1		1	6	10
2	1		2	5	10
2		15			17

Analog (4CIF)	IP SD (4CIF)	UltraView Camera (4CIF)	IP HD 720p (1280x720)	IP HD 2MPX (UXGA - 1600x1200@12.5fps max)	Max. Amt of cameras connected
0	16				16
0	8		4		12
0	8			4	12
0			8		8
0				8	8
0				8	8
0		16			16