

Micro Multi-purpose Panic Button

Water-resistant wireless device



OVERVIEW

The Interlogix Micro Multi-purpose Panic Button features an updated design that is both chlorine- and UV-resistant for longlasting and reliable performance. In addition, the Panic Button is water-resistant and functions as a wireless device used for activating police, fire or auxiliary alarms throughout the premises. When the panic button is pressed, the LED mounted under the front cover will blink and an alarm signal is transmitted.

The status of the battery is sent in every transmission, and the battery is field-replaceable. The button also has five adapters that easily fit onto the panic button. Using these adapters, the panic button can be mounted on the wall, worn as a belt clip, watch or pendant for maximum flexibility.

STANDARD FEATURES

- Activates police, fire or auxiliary alarms
- Works with all 319.5 MHz Learn Mode panels
- Water-resistant rating to IPX7 (1 meter for 30 minutes)
- Includes adapters for wall mounting or wearing as a belt clip, watch, or pendant

Specifications

All 319.5 MHz Learn Mode panels
One 3V Duracell® (DL2032) lithium battery
One module/panel communications status LED
319.5 MHz
At least 375 ft. (114 m) open-air range
32 to 120°F (0 to 49°C)
-30 to 140°F (-34 to 60°C)
90% relative humidity, noncondensing
Water-resistant rating to IPX7 (1 meter for 30 minutes)
FCC Part 15
$1.5 \times 1.3 \times .5$ in. (without adaptors or wristband)

Ordering Information

60-906-95 N

Micro Multi-Purpose Panic Button



interlogix.com

Specifications subject to change without notice.

© 2013 United Technologies Corporation. All rights reserved. Interlogix is part of UTC Climate, Controls & Security, a unit of United Technologies Corporation.

North America T 855-286-8889

Latin America T 561-998-6114

306-3689 2013/11 (75309)